

DIPLEXERS

Center Frequency 1 (MHz)	Part Number	Insertion Loss (dB)	VSWR (∞:1)	Rejection (dB) (1)	From (MHz) (1)	To (MHz) (1)	Center Frequency 2 (MHz)	Insertion Loss (dB)	VSWR (∞:1)	Rejection (dB) (2)	From (MHz) (2)	To (MHz) (2)
6.5	MUX-L-10701	1	1.92	90	10	32	29	1	1.92	90	5	8
15	TMX-L-14491	0.75	1.29	50	700	700	700	0.75	1.29	50	15	15
15	TMX-L-14497	1	1.29	50	50	50	50	1	1.29	50	15	15
17.5	MUX-L-10702	1	1.92	90	30	80	75	1	1.92	90	15	20
18	TMX-L-15094	2	1.5	20	30	30	239	2	1.5	20	14	14
27	TMX-L-14628	1	1.29	60	0	5	54	1	1.2	40	5	39
42	TMX-L-14488	1	1.2	60	54	870	54	1	1.5	40	5	420
42.5	MUX-L-10703	1	1.92	90	70	200	185	1	1.92	90	30	50
80	MUX-L-10704	1	1.92	90	120	400	360	1	1.92	90	60	100
88	TMX-L-15315	1	1.35	30	112	975	112	1	1.35	30	88	20
100	TMX-L-14660	3	1.5	50	125	125	150	3	1.5	50	125	125
125	MUX-L-10705	1	1.92	90	200	600	550	1	1.92	90	100	150
165	TMX-L-14498	1.5	1.92	25	200	200	200	1.5	1.92	25	165	165
165	TMX-L-14499	1.5	1.92	25	200	200	200	1.5	1.92	25	165	165
174	TMX-L-14336	2	1.38	3	154	154	350	2	1.38	3	330	330
200	TMX-L-15402	0.5	1.5	50	1200	2000	1200	0.7	1.5	50	0	250
287.5	TMX-L-15296	1.5	1.25	80	0	50	907.5	1.5	1.25	80	0	500
306	TMX-L-15367	1.3	1.5	70	70	70	1535	1.3	1.5			
335	MUX-L-10753	1	1.67	45	800		1535	1	1.67	45	400	
455	TMX-C-14676	3.3	1.5	60	465	465	465	3.3	1.5	60	455	455
624	MUX-L-10699	1	1.92	50	1100	2094	7550	1	1.92	60	550	698
680.5	MUX-C-10875-2	2	1.22	65	0	652	634.5	2	1.22	65	0	602
707	MUX-C-10711	2	1.5	90	0	628	737	2	1.5	90	0	708
789.5	MUX-C-10295	2.9	1.5	46	748		942.5	2.9	1.5	46	915	
807.5	MUX-L-10737	3	1.92	75	1400	3000	2200	3	1.92	75	700	915
1000	TMX-L-14978	3	1.288	40	1	675	1800	3	1.288	40	1	1150
1000	TMX-L-15177	5	1.43	61	2850	4375	4125	3	1.43	40	7750	8750
1000	TMX-L-15311	0.6	1.5	30	1200	1200	1200	0.6	1.5	30	1200	2500
1227	TMX-L-14543	0.5	1.35	35	2200	2500	1575	0.5	1.35	35	2200	2500
1227	TMX-C-14379	1.5	1.5	70	0	1177	1575	1.5	1.5	70	1630	3000
1227	TMX-C-14379	1.5	1.5	70	0	1177	1575	1.5	1.5	70	1630	3000
1227	TMX-C-14953	1	1.5	80	1172	1172	1575	1	1.5	80	1520	1520
1227.6	TMX-L-14785	3.5	1.5	54	1514	1600	1575.42	3.5	1.5	54	0	1289
1227.6	TMX-L-15401	2.5	1.5	3	1202.6	1202.6	1575.42	3	1.5	3	1550.42	1550.42
1350	MUX-L-11164	1.5	1.92	50	2000	10000	5500	2	1.92	70	0	1700
1395	TMX-L-15102	6	1.5	80	0	1300	745	6	1.5	72	0	652
1575	TMX-L-14629	1.5	1.5	40	1470	1470	1227	1.5	1.5	40	1177	1177

DIPLEXERS

Center Frequency 1 (MHz)	Part Number	Insertion Loss (dB)	VSWR (∞:1)	Rejection (dB) (1)	From (MHz) (1)	To (MHz) (1)	Center Frequency 2 (MHz)	Insertion Loss (dB)	VSWR (∞:1)	Rejection (dB) (2)	From (MHz) (2)	To (MHz) (2)
1575	TMX-L-14457	1.5	1.5	40	1470	1470	1227	1.5	1.5	40	1130	1130
1575	TMX-L-14682	1.5	1.4	40	1500	1500	1227	1.5	1.4	40	1152	1152
1575.4	TMX-L-15593	1.37	1.38	43	1321.6	1479.9	1227.6	1.2	1.38	43	100	1131.1
1575.4	TMX-L-15592	1.37	1.38	43	1321.6	1479.9	1227.6	1.2	1.38	43	100	1131.1
1575.42	TMX-C-14355	2.3	2	40	30	1445.42	1227.6	2.7	1.99	40	30	1097.6
1575.42	TMX-C-14979	1.5	1.5	40	1500.42	1500.42	1227.6	1.5	1.5	40	1152.6	1152.6
1575.42	TMX-C-15522	1.5	1.5	40	1500.42		1227.6	1.5	1.5	40	1152.6	
1745	MUX-C-10820	1.5	1.22				2155	1.5	1.22			
1745	MUX-C-10820	1.5	1.22	50	1710	6000	2155	1.5	1.22	50	1710	6000
1790	TMX-C-002-004-	1.5	1.35	10	1780	1780						
1790.344	TMX-C-14977	2.5	1.651	40	1	1567.594	2350.344	2.5	1.433	40	1	2090.344
1860	TMX-C-14677	2	1.5	65	1860	1860	1937.5	2	1.5	65	1865	1865
1882.5	MUX-C-10819	2.5	1.22	60	0	1835	1962.5	2.5	1.22	60	0	1915
1882.5	MUX-C-10819	2.5	1.22	60	0	1835	1962.5	2.5	1.22	60	0	1915
2067.5	MUX-C-10650	1	1.29	60	2200	2290	2245	1	1.29	60	2025	2110
2400	TMX-L-14742	1	2	60	6400	7750	6400	1	2	60	0	2400
3500	MUX-L-10700	1	1.92	50	6800	10800	10400	1	1.92	60	3400	3600
3579.344	TMX-C-14976	3	1.329	40	1	3464.594	3809.344	3	1.536	40	3694.094	3698.849
3600	TMX-I-15025		1.5				11000		1.5			
4500	TMX-C-14975	3	1.536	40	1	3150	7000	3	1.536	40	1	5700
5530.344	TMX-C-14974	2	1.433	28	1	5260.344	6990.344	2.4	1.377	28	1	6868.844
6800	TMX-L-14323	1.5	2				4750	1.5	2			
14507.5	TMX-W-14875	1.25	1.4	59	14150	14150	15087.5	1	1.4	20	15660	15660
