

CERAMIC FILTERS

Center Frequency (MHz)	Part Number	Bandwidth (MHz)	Insertion Loss (dB)	VSWR (:1)	Rejection (dB) (1)	From (MHz) (1)	To (MHz) (1)	Rejection (dB) (2)	From (MHz) (2)	To (MHz) (2)	Rejection (dB) (3)	From (MHz) (3)	To (MHz) (3)
611	TCR-C-14940	6	3.4	1.5	20	598	598	20	624	624			
857	TCR-C-14528	2	3	1.5	12	849	849	43	869	894	55	894	894
858	TCR-C-14725	10	4.68	2	20	868.87	868.87						
1000	TCR-C-14406	20	4	1.5	25	980	980	25	1020	1020	50	1300	2000
1080	TCR-C-14737	34	3.8	1.67	50	1024	1024	50	1136	1136			
1080	TCR-C-14738	6	5	1.67	40	1024	1024	40	1136	1136			
1080	TCR-C-14739	70	1.8	1.67	40	880	880	40	1280	1280			
1080	TCR-C-14643	60	3	1.67	13	1030	1030	13	1130	1130	50	980	980
1090	TCR-C-14705	10	3	1.5	70	1030	1030	60	1050	1050	70	1200	1200
1090	TCR-C-15108	6	1.2	1.5	15	1030	1030	15	1150	1150	30	970	970
1096.35	TCR-C-14565	84.82	2.5	1.5	40	1577.35	1577.35	40	1815.35	1815.35	50	1543.35	1543.35
1227	TCR-C-14100	20	2.4	1.5	24	1187	1187	24	1267	1267	45	1287	1287
1260	TCR-L-14639	36	3	1.45	60	1120	1120	60	1400	1400			
1276	TCR-C-14644	50	3	1.67	8	1231	1231	8	1321	1321	80	856	856
1296	TCR-C-14329		2	1.5	45	1152	1152	30	1224	1224	30	1368	1368
1310	TCR-C-14580	20	4.8	1.5	62.5	1190	1190	15	1282	1282	15	1338	1338
1310	TCR-C-14581	35	4.8	1.5	65	1190	119	12	1282	1282			
1332	TCR-C-14645	50	1	1.67	8	1287	1287	8	1377	1377	80	912	912
1346	TCR-C-14646	50	1	1.67	8	1301	1301	8	1391	1391	80	926	926
1391	TCR-C-14647	50	1	1.67	8	1345	1345	8	1436	1436	80	971	971
1413.5	TCR-C-14941	37	3.2	1.5	10	1385	1385	13	1442	1442			
1420	TCR-C-14648	50	1	1.67	8	1375	1375	8	1465	1465	80	1000	1000
1510	TCR-L-14638	48	2	1.45	55	1190	1190	50	1830	1830			
1512	TCR-L-14640	36	3	1.45	35	1402	1402	35	1622	1622	60	1332	1332
1520	TCR-C-14759	34	2.6	1.5	35	1450	1450	35	1590	1590			
1542	TCR-C-14408	40		1.5	40	1440	1440	25	1490	1490	25	1600	1600
1610	TCR-C-14649	50	1	1.67	8	1565	1565	8	1655	1655	80	1190	1190
1643	TCR-C-14654	100	1.5	1.5	25	1000	1000	25	2000	2000			
1643	TCR-C-14333	100	1.5	1.5	25	1500	1500	25	2000	2000			
1650	TCR-C-14715	20	4	1.5	30	1578	1578	30	1734	1734			
1690	TCR-C-14578	56	1.5	1.5	45	2040	2040						
1800	TCR-C-14710	50	4	1.5	60	0	1690	60	1910	5000			
1880	TCR-C-14854	60	2	1.5	20	1790	1790	20	1970	1970			
1880	TCR-C-15261	25	2.7	1.3	30	1850	1850	42	1840	1840	30	1915	1915
1880	TCR-C-15261	20	3	1.3	30	1850	1850	40	1840	1840	30	1915	1915
1960	TCR-C-14812	44	2	1.5	60	1490	1550	60	1710	1770			
1960	TCR-C-14946	60	2.5	1.4	8	1910	1910						
2000	TCR-C-14716	20	4	1.5	30	1907	1907	30	2110	2110			
2085	TCR-C-14754	4	10	1.43	40	2110	2170						
2100	TCR-C-14534	30	3	1.7	55	1900	1900	55	2300	2300			



CERAMIC FILTERS

Center Frequency (MHz)	Part Number	Bandwidth (MHz)	Insertion Loss (dB)	VSWR (___:1)	Rejection (dB) (1)	From (MHz) (1)	To (MHz) (1)	Rejection (dB) (2)	From (MHz) (2)	To (MHz) (2)	Rejection (dB) (3)	From (MHz) (3)	To (MHz) (3)
2100	TCR-C-14537	20	5	1.7	35	2020	2020	35	2170	2170	50	1800	1800
2180	TCR-C-14579	56	2.8	1.5	15	2124	2124	15	2238	2238			
2237.5	TCR-C-14566	111.88	2.5	1.5	40	2080.5	2080.5	40	2394.5	2394.5	50	2036.5	2036.5
2332	TCR-C-14942	65	1.6	1.5	30	2132	2132	30	2532	2532	10	2250	2250
2340	TCR-C-14551	120	1	1.67	8	2265	2265	8	2415	2415	80	1920	1920
2442	TCR-C-15516	100	1.5	1.29	50	0	2200	50	2700	5000			
2442.5	TCR-C-14325	90	1.4	1.5	30	2142.5	2142.5	30	2742.5	2742.5			0
2450	TCR-C-14634	200	3	1.7	30	2000	2000	20	2900	2900			
2524	TCR-C-14776	48	2.5	1.5	40	50	2160	20	2596	2596	40	3000	4000
2572	TCR-C-14777	48	2.5	1.5	40	50	2160	20	2644	2692	40	3000	4000
2600	TCR-C-14722	200	4.5	2	50	2500	2500	50	2700	2700			
2605	TCR-C-14617	130	1.4	1.5	30	2350	2350	30	3000	3000			
2620	TCR-C-14778	48	2.5	1.5	40	50	2280	20	2500	2548	40	3000	4000
2668	TCR-C-14779	48	2.5	1.5	40	50	2280	20	2548	2596	40	3000	4000
2745	TCR-C-14943	110	1	1.5	30	2485	2485	30	3005	3005	10	2250	2250
2745	TCR-C-14956	110	1.6	1.5	30	2485	2485	30	3005	3005	10	2250	2250
3465	TCR-C-14911	550	3	1.5	40	50	3080	15	3550	3600	40	4000	5000
3575	TCR-C-14910	450	3	1.5	15	3450	3500	20	3700	3700	40	4000	5000